

# CTC CONNECT



## WS100 Series ConnectSens™ Wireless Triaxial Accelerometer Installation Guide

## TABLE OF CONTENTS

- Introduction.....3
- Product Description.....3
- Battery Information .....4
- Mounting Instructions.....5
- Warranty and Refund..... 13

## INTRODUCTION


This document contains information on the installation of the WS100 Series of wireless triaxial sensors.

### WS100 Series Product Overview

CTC Connect WS100 Series Wireless Sensors periodically collect triaxial vibration data within a selected frequency band, as well as temperature measurements. From this vibration data, overall vibration amplitudes are calculated in RMS, peak, and peak-to-peak formats. This data is then transmitted through non-connectable **Bluetooth**® advertisements. Within a clear line of sight, they can transmit data as far as 2100 ft/640 m.


Data can be accessed via CTC ConnectView™ Web App running on a CTC Gateway, or through custom software integration with the CTC Connect API and CTC Gateway.

WS100 Series sensors are designed for permanent mounting on the machine surface. To prepare the machine surface for installation, spot face, drill, and tap the mounting location. CTC suggests using MH117 Series Installation Tool Kits. To view in depth mounting instructions, please view our Mounting Guide.



## BATTERY INSTALLATION

To avoid premature battery usage, CTC Wireless sensors ship with the battery disconnected. To install, remove the cap and connect the battery's connector to the receptacle on the back of the exposed circuit board. Tighten down the sensor cap and your sensor will now begin sending out Bluetooth® advertisements for discovery. CTC Gateways and the preloaded Web App will automatically be scanning for these advertisements when running, making all detected sensors visible.




# MOUNTING INSTRUCTIONS

## Stud Mounting


Please be aware that due to the WS100 Series Sensor being triaxial, stud mounting may present challenges in maintaining precise control over the orientation of the axes during mounting.

1. Spot face, drill, and tap the mounting location. CTC recommends MH117 Series Installation Tool Kits inclusive of spot face tools that are 1.25 inches in diameter:

PN	Spot Face Tool Type	Spot Face Diameter	Tap Thread
MH117-1B	High Speed Steel	1.25 in. (31.75 mm)	1/4-28
MH117-4B	High Speed Steel	1.25 in. (31.75 mm)	M6x1
MH117-6B	High Speed Steel	1.25 in. (31.75 mm)	M8x1.25
MH117-11B	Carbide Tipped	1.25 in. (31.75 mm)	1/4-28



2. Thread the sensor onto the machine using 2 to 5 ft-lbs of mounting force. A coupling agent (such as MH109-2A epoxy) will maximize the high-frequency response of your hardware but is not required. Ensure that once fully threaded, the mounting base of the WS100 is completely flush with the mounting surface.



**NOTE:** If the sensor is not tight enough, proper coupling between the base of the sensor and the mounting disk will not be achieved. If the sensor is over-tightened, stud failure may occur.

## Quick Disconnects with Adhesive Mounting Stud

1. Prepare the mounting location by spot facing using MH117 Series Installation Tool Kit spot face drills. For Quick Disconnect Studs, it's advisable to use tools with a diameter of at least one inch.

PN	Spot Face Tool Type	Spot Face Diameter
MH117-3A	High Speed Steel	1.0 in. (25.4 mm)
MH117-13A	Carbide Tipped	1.0 in. (25.4 mm)



2. Remove the stud adapter from the sensor. Using a 3/16 in. allen wrench, loosely thread the MH107-3A receptacle onto the base of the sensor. Align the receptacle with the axes of the sensor and attach securely. It is recommended to align the thumbgrip of the receptacle with the Y axis of the sensor, and the locator notch with the X axis.




3. Place the sensor and receptacle assembly onto the MH107-1B Quick Disconnect stud by aligning the locator notches on each mounting piece, then give a quarter turn clockwise. If using the alignment method above, this will place the Y axis of the sensor over the locator notch of the stud.
4. Place the entire sensor assembly onto the prepared machine surface. Use a marker to indicate the landing points of each axis.

5. Disconnect the mounting stud. Apply epoxy (suggested MH109-2A) to the roughened surface on the bottom of the stud.




*Without Epoxy*




*With Epoxy*

6. Affix the stud to the mounting location, ensuring alignment with the desired axis orientations.




7. After the stud has fully adhered to the machine, proceed to attach the sensor and receptacle assembly securely.



## Quick Disconnects With Through Hole Mounting Stud

1. Spot face, drill, and tap the mounting location. CTC recommends MH117 Series Installation Tool Kits inclusive of spot face tools that are at least one inch in diameter:

PN	Spot Face Tool Type	Spot Face Diameter	Tap Thread
MH117-3A	High Speed Steel	1.0 in. (25.4 mm)	1/4-28
MH117-7A	High Speed Steel	1.0 in. (25.4 mm)	M6x1
MH117-13A	Carbide Tipped	1.0 in. (25.4 mm)	M6x1




2. Remove the stud adapter from the sensor. Using a 3/16 in. allen wrench, loosely thread the MH107-3A receptacle into the base of the sensor. Align the receptacle with the axes of the sensor and attach securely.



3. Place the sensor and receptacle assembly onto the Quick Disconnect stud by aligning the locator notches on each mounting piece, then give a quarter turn clockwise. If using the alignment method above, this will place the Y axis of the sensor over the locator notch of the stud.
4. Place the entire sensor assembly onto the prepared machine surface. Use a marker to indicate the landing points of each axis.



5. Disconnect the mounting stud. Insert the through bolt into the top of the stud.
6. Affix the stud to the mounting location by tightening down the through bolt, ensuring alignment with the desired axis orientations.



7. After the stud is fully adhered to the machine, proceed to attach the sensor and receptacle assembly securely.



## Adhesive Mounting Pads


CTC recommends using MH130-3A Adhesive Mounting Disk with ¼-28 blind tapped hole.

1. Prepare the mounting location by spot facing using MH117 Series Installation Tool Kit spot face drills. For the MH130-3A, it's advisable to use tools with a diameter of 1.25 inches:


PN	Spot Face Tool Type	Spot Face Diameter
MH117-1A	High Speed Steel	1.25 in. (31.75 mm)
MH117-11a	Carbide Tipped	1.25 in. (31.75 mm)



2. Thread the sensor fully onto the mounting pad. Use a marker to indicate the landing points of each axis on the mounting pad. Once complete, unthread the sensor.
3. Apply epoxy (suggested MH109-2A) to the roughened surface on the bottom of the mounting pad.




***Without Epoxy***




***With Epoxy***

4. Affix the mounting pad to the mounting location, ensuring alignment with the desired axis orientations.



5. After the mounting pad has fully adhered to the machine, proceed to attach the sensor and stud to the mounting pad and **tighten securely**, approximately 2 to 5 ft. lbs.



### Adjustable Orientation Magnetic Mounting Base

1. Insert the provided allen wrench into the socket on the bottom of the MH214-3A magnet.



2. Holding the magnet and wrench in one hand, thread the sensor and stud onto the front of the magnet until sensor and magnet make loose contact. Remove the allen wrench.



3. Align the the axes of the sensor as desired with respect to the rails of the magnet. Reinsert the allen wrench, and tighten the entire assembly.



4. Gently rock the sensor and magnet assembly onto the machine at the intended location.



## Magnetic Mounting Base

1. Thread the sensor and stud onto the MH114-3A magnet.



2. Gently rock the sensor and magnet assembly onto the machine at the intended location, ensuring that the axes of the sensor are in the intended alignment with the machine.



## WARRANTY AND REFUND

Please visit [www.ctconline.com](http://www.ctconline.com) to view a complete recapitulation of our warranty and refund policies.

The Bluetooth® word mark and logos are registered trademarks owned by Bluetooth SIG, Inc. and any use of such marks by Connection Technology Center, Inc. (CTC) is under license. Other trademarks and trade names are those of their respective owners.

